



ACPS3310 CompactPCI-Serial AcroPack Carrier Board

USER'S MANUAL

ACROMAG INCORPORATED
30765 South Wixom Road
Wixom, MI 48393-2417 U.S.A.
Tel: (248) 295-0310
Email: solutions@acromag.com

Copyright 2019, Acromag, Inc., Printed in the USA.
Data and specifications are subject to change without notice.

8501136A

Table of Contents

1.	GENERAL INFORMATION	4
	Intended Audience	4
	Preface.....	4
	Trademark, Trade Name and Copyright Information.....	4
	Radio Frequency Interference Statement	4
	Environmental Protection Statement	4
	ACPS3310 Overview	4
	KEY ACPS3310 FEATURES	5
	SIGNAL INTERFACE PRODUCTS.....	5
	Cable.....	5
	Termination Panel	6
	Software Support.....	6
	Windows®	6
	VxWorks®	6
	Linux®	6
2.	PREPARATION FOR USE	7
	UNPACKING AND INSPECTION	7
	BOARD CONFIGURATION	7
	Power and Cooling Considerations	8
	Carrier Fuses.....	9
	Isolation Considerations.....	9
	Isolated Power.....	9
	ACROPACK MODULE INSTALLATION	10
	FIELD GROUNDING CONSIDERATIONS	10
	CONNECTORS	11
	Front Panel Field I/O Connectors	11
	AcroPack Field I/O Connectors.....	11
	Mini-PCIe Connectors.....	14
	CompactPCI-Serial Backplane Connections.....	15
	JTAG Programming/Debug Connector	16
3.	THEORY OF OPERATION	17
	PCIe Switch	18
	DC/DC Converter	18
	Slot Addressing.....	18
	JTAG.....	19

	Power Supply Fuses.....	19
4.	SERVICE AND REPAIR.....	19
	PRELIMINARY SERVICE PROCEDURE	19
	WHERE TO GET HELP	19
5.	SPECIFICATIONS.....	20
	PHYSICAL.....	20
	Physical Configuration.....	20
	Connectors	20
	Isolation.....	20
	Isolated Power.....	21
	Power	21
	Fuses.....	21
	CPCI-S COMPLIANCE	21
	ENVIRONMENTAL	21
	EMC Compliance	22
	Vibration and Shock Standard.....	22
	Reliability Prediction	22
6.	CERTIFICATE OF VOLATILITY	23
7.	REVISION HISTORY.....	24

1. GENERAL INFORMATION

Intended Audience

This users' manual was written for technically qualified personnel who will be working with I/O devices using the AcroPack module.

Preface

The information contained in this manual is subject to change without notice, and Acromag, Inc. (Acromag) does not guarantee its accuracy. Acromag makes no warranty of any kind with regard to this material, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose. Further, Acromag assumes no responsibility for any errors that may appear in this manual and makes no commitment to update, or keep current, the information contained in this manual. No part of this manual may be copied or reproduced in any form, without the prior written consent of Acromag.

Trademark, Trade Name and Copyright Information

© 2019 by Acromag Incorporated.

All rights reserved. Acromag and Xembedded are registered trademarks of Acromag Incorporated. All other trademarks, registered trademarks, trade names, and service marks are the property of their respective owners.

Radio Frequency Interference Statement

This is a Class A product. In a domestic environment this product may cause radio interference, in which case the user may find it necessary to take adequate corrective measures.

Environmental Protection Statement

This product has been manufactured to satisfy environmental protection requirements where possible. Many components used (structural parts, circuit boards, connectors, etc.) are capable of being recycled. Final disposition of this product after its service life must be conducted in accordance with applicable country, state, or local laws or regulations.

ACPS3310 Overview

The ACPS3310 is a Compact Peripheral Component Interconnect – Serial (CPCI-S) card and is a carrier for mini-PCIe or AcroPack mezzanine modules. This carrier board provides a modular approach to system assembly, since each carrier can be populated with any combination of analog input/output, digital input/output, communication, etc. AcroPack modules. Thus, the user can create a board which is customized to the application. This saves money and space - a single carrier board populated with AcroPack modules may

replace several dedicated function PCI or PCIe bus boards. The ACPS3310 non-intelligent carrier board provides impressive functionality at low cost.

Model	Input/Output	AcroPack Slots	Operating Temperature Range
ACPS3310	Front I/O	2 (A, B)	-40 to +85°C (with 200 LFM airflow)

KEY ACPS3310 FEATURES

Interface for AcroPack modules – The ACPS3310 provides an electrical and mechanical interface for up to two industry standard mini-PCIe or AcroPack modules. AcroPack modules are available from Acromag. Mini-PCIe cards are available from other vendors in a wide variety of input/output configurations to meet the needs of varied applications.

PCI Express Version 2.1 Compliant Carrier: - Includes a PCIe switch to allow two PCIe devices (AcroPack or mini-PCIe) to share a single 4HP peripheral board slot in a CPCI-S chassis.

Board Identification – A unique carrier and site number is determined from geographical addressing signals GA0-GA3 from the backplane. This feature provides the capability to distinguish a particular carrier and AcroPack module from others when multiple instances of the same carrier and/or module are used in a system.

JTAG Programming Header – A standard 14-pin Xilinx JTAG programming header is provided for programming and debugging the FPGA on some AcroPack modules. The JTAG ports of the two AcroPack modules are daisy-chained.

Individually Fused Power - Fused +1.5V, +3.3V, +5V, +12V, and -12V DC power is provided. A fuse is present on each supply line serving each AcroPack module. Fuses F1-F3 and F7-F9 are user replaceable. Fuses F4-F6 and F10-F12 are not user replaceable, you must return the board to Acromag to replace these fuses.

SIGNAL INTERFACE PRODUCTS

This AcroPack carrier board will mate directly to all industry standard mini-PCIe and AcroPack modules. Acromag provides the following interface products (all connections to field signals are made through the carrier board which passes them to the individual AcroPack modules):

Cable

Model 5028-420 Round cable, shielded, 34 twisted pairs, male SCSI-3 connector to 68-pin CHAMP 0.8mm, 2 meters long.

Model 5028-615 Cable, 68-pin CHAMP to pigtail, 36 inches long.

Model 5028-616 Cable, 68-pin CHAMP to pigtail, 70 inches long.

Termination Panel

Model 5025-288 DIN-rail mountable panel provides 68 screw terminals for universal field I/O termination, SCSI-3 connector.

Software Support

The AcroPack series products require support drivers specific to your operating system. Supported operating systems include: Linux®, Windows®, and VxWorks®.

Windows®

Acromag provides software products (sold separately) to facilitate the development of Windows® applications interfacing with AcroPack modules. This software (model APSW-API-WIN) consists of low-level drivers and Dynamic Link Libraries (DLLs) that are compatible with a number of programming environments. The DLL functions provide a high-level interface to boards eliminating the need to perform low-level reads/writes of registers, and the writing of interrupt handlers.

VxWorks®


Acromag provides a software product (sold separately) consisting of VxWorks® software. This software (Model APSW-API-VXW) is composed of VxWorks® (real time operating system) libraries for all AcroPack modules, VPX I/O board products, and PCIe I/O Cards. The software is implemented as a library of “C” functions which link with existing user code to make possible simple control of all Acromag AcroPack modules.

Linux®

Acromag provides a software product consisting of Linux® software. This software (Model APSW-API-LNX) is composed of Linux® libraries for all AcroPack modules, VPX I/O board products, and PCIe I/O Cards. The software is implemented as a library of “C” functions which link with existing user code to make possible simple control of all Acromag AcroPack modules.

2. PREPARATION FOR USE

IMPORTANT PERSONAL AND PRODUCT SAFETY CONSIDERATIONS



It is very important for the user to consider the possible safety implications of power, wiring, component, sensor, or software failures in designing any type of control or monitoring system. This is especially important where personal injury or the loss of economic property or human life is possible. It is important that the user employ satisfactory overall system design. It is understood and agreed by the Buyer and Acromag that this is the Buyer's responsibility.



WARNING: This board utilizes static sensitive components and should only be handled at a static-safe workstation. This product is an electrostatic sensitive device and is packaged accordingly. Do not open or handle this product except at an electrostatic-free workstation. Additionally, do not ship or store this product near strong electrostatic, electromagnetic, magnetic, or radioactive fields unless the device is contained within its original manufacturer's packaging. Be aware that failure to comply with these guidelines will void the Acromag Limited Warranty.

UNPACKING AND INSPECTION

Upon receipt of this product, inspect the shipping carton for evidence of mishandling during transit. If the shipping carton is badly damaged or water stained, request that the carrier's agent be present when the carton is opened. If the carrier's agent is absent when the carton is opened, and the contents of the carton are damaged, keep the carton and packing material for the agent's inspection.

For repairs to a product damaged in shipment, refer to the Acromag Service Policy to obtain return instructions. It is suggested that salvageable shipping cartons and packing material be saved for future use in the event the product must be shipped.

This board is physically protected with packing material and electrically protected with an anti-static bag during shipment. It is recommended that the board be visually inspected for evidence of mishandling prior to applying power.

The board utilizes static sensitive components and should only be handled at a static-safe workstation.

BOARD CONFIGURATION

Power should be removed from the carrier board when installing AcroPack modules, cables, termination panels, and field wiring.




Figure 1 Connector and Fuse Locations

Power and Cooling Considerations

Refer to the specifications for loading and power requirements. Be sure that the system power supplies are able to accommodate the power requirements of the carrier board, plus the installed AcroPack modules within the voltage tolerances specified.

IMPORTANT: Adequate air circulation must be provided to prevent a temperature rise above the maximum operating temperature.

The lack of air circulation within some CPCI-S chassis could be a cause for some concern. The dense packing of the AcroPack modules to the carrier board alone results in elevated module and carrier board temperatures, and the restricted air flow within the chassis aggravates this problem. Adequate air circulation must be provided to prevent a temperature rise above the maximum operating temperature and to prolong the life of the electronics. If the installation is in an industrial environment and the board is exposed to environmental air, careful consideration should be given to air-filtering.

Carrier Fuses

CAUTION: Acromag has used pins labeled as reserved in the Mini-PCle specification for additional power connections. If you are installing a Mini-PCle card from another manufacturer in slot A remove fuses F1(+12V), F2(+5V) and F3 (-12V). When installing a Mini-PCle card in from another manufacturer in slot B remove fuses F7(+12V), F8(+5V) and F9 (-12V). Fuse locations are shown in Figure 1.

Other fuses present on the board include +1.5V Fuses F6 (slot A) and F12 (slot B). Also present on the board are +3.3V Fuses F4 (slot A) and F10 (slot B). These fuses are not user replaceable. Return the carrier board to Acromag to replace these fuses. Both Mini-PCle cards from other manufacturers and the AcroPack modules can use +1.5V and +3.3V power.

Fuses not present on the board include +3.3V Aux Fuses F5 (slot A), F11 (slot B). Some standard Mini PCle cards may require +3.3V Aux to power the module. For a site using such a module the +3.3V fuse will need to be removed and the +3.3 Aux fuse will need to be installed, along with a regulator to convert +5V standby from the CPCI-S backplane to +3.3V Aux. Return the carrier board to Acromag to remove and install these parts.

Isolation Considerations

WARNING: This AcroPack carrier is designed to provide isolation between the AcroPack Field I/O signals and the host. The AcroPack module must also be an isolated AcroPack module to maintain the isolation between the logic and field I/O signals. Unless isolation is provided on the AcroPack module itself, the field I/O connections are not isolated from the PCIe bus.

When this carrier is used with isolated AcroPack modules, both AcroPacks in slots A and B should be isolated. Non-isolated AcroPacks sharing the same Connector will compromise the isolation integrity of the other AcroPack.

Isolated Power

The use of an optional isolated DC/DC Converter is required for use with a few of Acromag's isolated AcroPack modules. See Figure 1 for carrier board location allocated for the isolated DC/DC converter corresponding to each slot.

The power supplies of one AcroPack site must be isolated from the power supplies of other AcroPack sites. The two separate isolated DC/DC converters make this possible. The DC/DC converted should only be populated on the carrier for AcroPacks needing the isolated power. Each isolated AcroPack module will list the requirement of the external DC/DC converter if needed.

The isolated DC/DC converter provide dual +12V and -12V power to the AcroPack module on field I/O pins 49 and 50 as listed in the Table below.

Table 1 Carrier Isolated Power

Supply Voltage	Current (Min)	Field I/O Pin
+12V +/- 8% (max)	0.16 A	50 ¹

Supply Voltage	Current (Min)	Field I/O Pin
-12V +/- 8% (max)	0.16 A	49 ¹
Return (GND)	1 A	48 ¹

Note 1: AcroPack carriers without provisions for the isolated power supplies can provide external power from the field power to the AcroPack module on pins 48, 49 and 50.

ACROPACK MODULE INSTALLATION

Power should be removed from the carrier board when installing AcroPack modules, cables, termination panels, and field wiring. Refer to Figure 2 while reading this section. To install, first insert the edge of the AcroPack module into the carrier connector at an angle similar to that shown in the figure. Next, using a rocking motion while gently applying force to keep the edge of the board against the back of the carrier connector, position the module such that the field I/O connector is just above the mating connector. Verify that the two connectors are properly aligned. Once alignment is achieved, you can fully seat the connector. It will snap into place. Install two M2.5 screws as shown.




Figure 2 AcroPack Module Installation

FIELD GROUNDING CONSIDERATIONS

The Field I/O signals are isolated from chassis and system ground on the carrier. However, some AcroPack modules connect Field I/O ground to system ground. Care should be taken in designing installations without isolation to avoid ground loops and noise pickup. This is particularly important for analog I/O applications when a high level of accuracy/resolution is needed (12-bits or more). Contact your Acromag representative for information on our many isolated signal conditioning products that could be used to interface to the AcroPack input/output modules.

CONNECTORS

The ACPS3310 carrier uses two AcroPack module field I/O connectors, two mini-PCIe connectors, two field I/O Champ connectors and one CompactPCI-Serial backplane connector. These are discussed in the following sections.

Front Panel Field I/O Connectors

Field I/O connections are made via one 68 pin, stacked, 0.8 mm Champ cable connector mounted on the front panel. The AcroPack module identifier (A and B) is marked on the front panel for easy identification. Cables and termination panels (or user defined terminations) can be quickly mated to the field I/O connectors. Pin assignments are defined by the installed AcroPack module.

AcroPack Field I/O Connectors

The field side connector of AcroPack modules mate to Samtec SS5-50-3.00-L-D-K-TR socket connectors on the carrier board.

This provides excellent connection integrity due to the gold plating in the mating area. M2.5 screws and spacers provide additional stability for harsh environments.

The functions of each of the Field I/O signals are defined by the installed AcroPack model.

Table 2 Field I/O Pin Assignments

Carrier J3 and Termination Panel	Carrier P7, P8	Module Pin Number	Field I/O Signal
1	2	2	Field I/O 1
35	1	1	Field I/O 2
	4	4	Reserved/isolation
	3	3	Reserved/isolation
2	6	6	Field I/O 3
36	5	5	Field I/O 4
	8	8	Reserved/isolation
	7	7	Reserved/isolation
3	10	10	Field I/O 5
37	9	9	Field I/O 6
	12	12	Reserved/isolation
	11	11	Reserved/isolation
4	14	14	Field I/O 7
38	13	13	Field I/O 8
	16	16	Reserved/isolation
	15	15	Reserved/isolation

Carrier J3 and Termination Panel	Carrier P7, P8	Module Pin Number	Field I/O Signal
5	18	18	Field I/O 9
39	17	17	Field I/O 10
	20	20	Reserved/isolation
	19	19	Reserved/isolation
6	22	22	Field I/O 11
40	21	21	Field I/O 12
	24	24	Reserved/isolation
	23	23	Reserved/isolation
7	26	26	Field I/O 13
41	25	25	Field I/O 14
	28	28	Reserved/isolation
	27	27	Reserved/isolation
8	30	30	Field I/O 15
42	29	29	Field I/O 16
	32	32	Reserved/isolation
	31	31	Reserved/isolation
9	34	34	Field I/O 17
43	33	33	Field I/O 18
	36	36	Reserved/isolation
	35	35	Reserved/isolation
10	38	38	Field I/O 19
44	37	37	Field I/O 20
	40	40	Reserved/isolation
	39	39	Reserved/isolation
11	42	42	Field I/O 21
45	41	41	Field I/O 22
	44	44	Reserved/isolation
	43	43	Reserved/isolation
12	46	46	Field I/O 23
46	45	45	Field I/O 24
	48	48	Reserved/isolation
	47	47	Reserved/isolation
13	50	50	Field I/O 25
47	49	49	Field I/O 26
	52	52	Reserved/isolation

Carrier J3 and Termination Panel	Carrier P7, P8	Module Pin Number	Field I/O Signal
	51	51	Reserved/isolation
14	54	54	Field I/O 27
48	53	53	Field I/O 28
	56	56	Reserved/isolation
	55	55	Reserved/isolation
15	58	58	Field I/O 29
49	57	57	Field I/O 30
	60	60	Reserved/isolation
	59	59	Reserved/isolation
16	62	62	Field I/O 31
50	61	61	Field I/O 32
	64	64	Reserved/isolation
	63	63	Reserved/isolation
17	66	66	Field I/O 33
51	65	65	Field I/O 34
	68	68	Reserved/isolation
	67	67	Reserved/isolation
18	70	70	Field I/O 35
52	69	69	Field I/O 36
	72	72	Reserved/isolation
	71	71	Reserved/isolation
19	74	74	Field I/O 37
53	73	73	Field I/O 38
	76	76	Reserved/isolation
	75	75	Reserved/isolation
20	78	78	Field I/O 39
54	77	77	Field I/O 40
	80	80	Reserved/isolation
	79	79	Reserved/isolation
21	82	82	Field I/O 41
55	81	81	Field I/O 42
	84	84	Reserved/isolation
	83	83	Reserved/isolation
22	86	86	Field I/O 43
56	85	85	Field I/O 44

Carrier J3 and Termination Panel	Carrier P7, P8	Module Pin Number	Field I/O Signal
	88	88	Reserved/isolation
	87	87	Reserved/isolation
23	90	90	Field I/O 45
57	89	89	Field I/O 46
	92	92	Reserved/isolation
	91	91	Reserved/isolation
24	94	94	Field I/O 47
58	93	93	Field I/O 48
	96	96	Reserved/isolation
	95	95	Reserved/isolation
25	98	98	Field I/O 49
59	97	97	Field I/O 50
	100	100	Reserved/isolation
	99	99	Reserved/isolation

Mini-PCle Connectors

The AcroPack Mini-PCle connectors mate to TE Connectivity 1759457-1 connectors on the carrier board. AcroPack locations are labeled on the board for easy identification.

Pin assignments for these connectors are based on the Mini-PCle specification with the exceptions noted in Table 3.

Table 3 Mini-PCIe Connectors J1 and J2 Pin Assignments

Pin #	Name	Pin #	Name
51	+5V ³	52	+3.3V ⁴
49	+12V ³	50	GND
47	-12V ³	48	+1.5V
45	Present	46	N.C. (LED_WPAN#) ¹
43	GND	44	N.C. (LED_WLAN#) ¹
41	+3.3V ⁴	42	N.C. (LED_WWAN#) ¹
39	+3.3V ⁴	40	GND
37	GND	38	USB_D+ ⁶
35	GND	36	USB_D- ⁶
33	PETp0	34	GND
31	PETn0	32	SMB_DATA ⁵
29	GND	30	SMB_CLK ⁵
27	GND	28	+1.5V
25	PERp0	26	GND
23	PERn0	24	+3.3V ⁴
21	GND	22	PERST#
19	TDI (UIM_C4) ^{1,2}	20	N.C. (W_DISABLE#) ¹
17	TDO (UIM_C8) ^{1,2}	18	GND
15	GND	16	UIM_VPP ¹
13	RECLK+	14	UIM_RESET ¹
11	REFCLK-	12	UIM_CLK ¹
9	GND	10	UIM_DATA ¹
7	CLKREQ#	8	UIM_PWR ¹
5	TCK (COEX2) ¹	6	+1.5V
3	TMS (COEX1) ¹	4	GND
1	N.C. (WAKE#) ¹	2	+3.3V ⁴

Notes:

1. The following mini-PCIe signals are not supported: WAKE#, LED_WPAN#, LED_WLAN#, LED_WWAN#, W_DISABLE#, COEX1, COEX2, UIM_C4, UIM_C8, UIM_VPP, UIM_RESET, UIM_CLK, UIM_DATA, UIM_PWR.
2. TDI is tied to TDO on modules that do not use JTAG.
3. +5, +12, and -12 Volt power supplies have been assigned to pins that are reserved in the mini-PCIe specification. Remove the fuses on these power supplies for mini-PCIe cards from other vendors that cannot tolerate power applied to these reserved pins.
4. All +3.3Vaux power pins are changed to system +3.3V power.
5. The SM bus signals SMB_CLK and SMB_DATA are used to communicate with a CPLD on the carrier that reports slot ID. These signals will be under the control of the AcroPack module.
6. USB_D+ and USB_D- is N.C. on AcroPack/mini-PCIe site A and connected to CPCI-S connector P1 to support USB-based mPCIe cards in AcroPack/mini-PCIe site B.

CompactPCI-Serial Backplane Connections

Table 4 indicates the pin assignments for the CPCI-S signals on the backplane connector P1.

Refer to the PICMG CPCI-S specification for additional information on the CPCI-S signals.

Table 4 CPCI-S P1 CONNECTIONS

Pin	A	B	C
01	+12V	STANDBY	GND
02	GND	I ² C_SCL	I ² C_SDA
03	1_USB3_Tx+	1_USB3_Tx-	GA0
04	GND	1_USB2+	1_USB2-
05	1_PE_Tx00+	1_PE_Tx00-	GND
06	GND	1_PE_Tx02+	1_PE_Tx02-
	D	E	F
01	+12V	+12V	GND
02	GND	reserved	reserved
03	1_USB3_Rx+	1_USB3_Rx-	GA1
04	GND	PE_CLKIN+	PE_CLKIN-
05	1_PE_Rx00+	1_PE_Rx00-	GND
06	GND	1_PE_Rx02+	1_PE_Rx02-
	G	H	I
01	+12V	+12V	GND
02	GND	RST#	WAKE_OUT#
03	SATA_SDI	SATA_SDO	GA2
04	GND	1_SATA_Tx+	1_SATA_Tx-
05	1_PE_Tx01+	1_PE_Tx01-	GND
06	GND	1_PE_Tx03+	1_PE_Tx03-
	J	K	L
01	+12V	+12V	GND
02	GND	PCIE_EN#	SYSEN#
03	SATA_SCL	SATA_SL	GA3
04	GND	1_SATA_Rx+	1_SATA_Rx-
05	1_PE_Rx01+	1_PE_Rx01-	GND
06	GND	1_PE_Rx03+	1_PE_Rx03-

Notes (Table 4):

1. Hash (#) is used to indicate an active-low signal.
2. BOLD ITALIC Logic Lines are NOT USED by the carrier board.

JTAG Programming/Debug Connector

A JTAG programming/debug connector is provided for developing applications that use Acromag's FPGA AcroPack modules. See reference designator P9 in




Figure 1. This is a standard 14-pin Xilinx programming header for connecting a Xilinx Platform USB II programming device (or equivalent). The pin assignment for P9 is shown in Table 5. A bypass circuit is included that will detect a vacant AcroPack site and close a switch to bypass the TDI and TDO signals. A CPLD on the carrier is included in the JTAG chain. The Xilinx Vivado tools can detect the presence of the CPLD in the JTAG chain and skip it when accessing the FPGAs on the AcroPack modules.

Table 5 JTAG Programming/Debug Connector Pin Assignment

Signal	Pin	Pin	Signal
N.C. ¹	1	2	_+3.3V
GND	3	4	TMS
GND	5	6	TCK
GND	7	8	TDO
GND	9	10	TDI
GND	11	12	N.C. ¹
N.C. ¹	13	14	N.C. ¹

Notes:

1. N.C. – not connected

TMS – JTAG Test Mode Select. This pin is the JTAG mode signal establishing appropriate TAP state transitions for target ISP devices sharing the same data stream.

TCK – JTAG Test Clock. This pin is the clock signal for JTAG operations and should be connected to the TCK pin on all target ISP devices sharing the same data stream.

TDO – JTAG Test Data Out. This pin is the serial data stream received from the TDO pin on the last device in a JTAG chain.

TDI – JTAG Test Data In. This pin outputs the serial data stream transmitted to the TDI pin on the first device in a JTAG chain.

+3.3V – The target reference voltage V_{REF} is 3.3 Volts

GND - Ground.

3. THEORY OF OPERATION

This section describes the functionality of the circuitry used on the carrier board. Refer to Figure 3 as you read this section.




Figure 3 ACPS3310 AcroPack Carrier Block Diagram

PCIe Switch

The PCIe switch is a 6 port 8 lane PCIe Gen 2 switch. It expands the single host PCIe port to two ports, one for each AcroPack site. The host port consists of four PCIe lanes or one PCIe lane (depending on CPCI-S slot), each of the AcroPack sites have one lane each.

Important Note: The ACPS3310 board is not hot-swappable.

DC/DC Converter

The ACPS3310 has four DC/DC converters to provide the power supply voltages to the AcroPack modules that are not present on the CPCI-S backplane. The +3.3 Volt, +5 Volt and -12 Volt supplies are sourced from +12 Volt power. The +1.5 Volt supply is sourced from the +3.3 Volt supply. Also, if the regulator is populated, +5V standby from the backplane will be converted to +3.3V Aux. This part is not populated by default.

Slot Addressing

The ACPS3310 carrier unique slot address is dependent upon the geographical addressing signals (GA0-GA3) from the backplane. The slot address is 5 bits long and consists of 1 bit to identify the site on the carrier where the AcroPack modules is installed and 4 bits that are determined by the GA signals. The CPLD will serialize the slot address and transmit the address to the AcroPack module as requested by the AcroPack module. The process of reading the slot address is typically initiated by host software.

JTAG

A JTAG interface is provided for programming and debugging FPGAs on AcroPack modules. It is intended to be used with a Xilinx Platform USB II programming device. A bypass circuit is included that will detect a vacant AcroPack site and close a switch to complete the JTAG chain. When two AcroPack modules with Xilinx FPGAs are installed on the carrier the module in slot B appears first in the chain followed by the module in slot A. The slot address CPLD is also included in the JTAG chain for factory programming.

Power Supply Fuses

The power supplies to each AcroPack module are individually fused. A blown fuse can be identified by visible inspection or by use of an ohm meter. The

fuse locations are shown in




Figure 1. The current rating for each of the fuses is listed in the Fuses paragraph in section 5.

4. SERVICE AND REPAIR

Surface-Mounted Technology (SMT) boards are generally difficult to repair. It is highly recommended that a non-functioning board be returned to Acromag for repair. The board can be damaged unless special SMT repair and service tools are used. Further, Acromag has automated test equipment that thoroughly checks the performance of each board.

Please refer to Acromag's Service Policy Bulletin or contact Acromag for complete details on how to obtain parts and repair.

PRELIMINARY SERVICE PROCEDURE

Before beginning repair, be sure that all the procedures in Section 2, Preparation for Use, have been followed. Also, refer to the documentation of your carrier board to verify that it is correctly configured. Replacement of the module with one that is known to work correctly is a good technique to isolate a faulty module.

CAUTION: POWER MUST BE TURNED OFF BEFORE REMOVING OR INSERTING BOARDS
--

WHERE TO GET HELP

If you continue to have problems, your next step should be to visit the Acromag website at <https://www.acromag.com>. Our website contains the most up-to-date product and software information.

Go to the “Support” tab or your specific AcroPack model ordering page.

Acromag’s application engineers can also be contacted directly for technical assistance via email, telephone, or FAX through the contact information listed below. Note that an email question can also be submitted from within the Knowledge Base or directly from the “Contact Us” tab. When needed, complete repair services are also available.

Phone: 248-295-0310

Email: solutions@acromag.com

5. SPECIFICATIONS

PHYSICAL

Physical Configuration

Length (ACPS3310)	6.299 inches (160.00 mm)
Height.....	3.937 inches (100.00 mm)
Board thickness.....	0.063 inches (1.60 mm)
Max component height	0.402 inches (10.21 mm)
Max component height under AcroPack modules	
	0.0789 inches (2.00 mm)
Weight.....	5.57 oz. (158 g)

Connectors

P1 (CPCI-S)	72-pin header, AIRMAX (Amphenol 10052825-101LF)
J3 (Carrier Field I/O).....	68-pin, Stacked, Champ (TE Connectivity 5787962)
P7, 8 (AcroPack Field I/O)	100-pin socket (Samtec SS5-50-3.00-L-D-K-TR)
J1, 2 (Mini-PCIe).....	52-pin socket (TE Connectivity 1759457-1)
P9 (JTAG).....	14-pin header (Molex 87832-1420)

Isolation

This AcroPack carrier is designed to provide isolation between the AcroPack Field I/O signals and the host. The AcroPack module must also be an isolated AcroPack module to maintain the isolation between the logic and field I/O signals. Unless isolation is provided on the AcroPack module itself, the field I/O connections are not isolated from the PCIe bus.

Host logic and field I/O are isolated from each other for voltages up to 250VAC or DC on a continuous basis (unit will withstand a 1500V AC dielectric strength test for one minute without breakdown). The carrier is designed to be used with isolated AcroPack modules.

The carrier also provides 100VAC or DC on a continuous basis between the signals of different AcroPack modules.

Due to the spacing between the pads of the 68-pin Champ connector and cable, the isolation between adjacent pins/signals on the front I/O is 30 V.

When this carrier is used with isolated AcroPack modules, both AcroPacks in slots A and B should be isolated AcroPacks. Non-isolated AcroPacks sharing the same connector will compromise the isolation integrity of the other AcroPack.

Isolated Power

The use of an optional isolated DC/DC Converter is required for use with isolated Acromag AcroPack modules. See section 2 and Figure 1 for carrier board locations of the isolated DC/DC converters corresponding to each AcroPack module.

Compatible DC/DC isolated converter modules are listed below:

DELTA DH06S/D Series, 6 Watt (+/- 12 VDC +/- 250mA), DH06D1212A

XP Power JCE Series, 6 Watt (+/- 12 VDC +/- 250mA), JCE0612D12

TRACO POWER, TEN 6N Series, 6 Watt (+/-12 VDC +/-250mA), TEN 6-1222N

Power

Board power requirements are a function of the installed AcroPack modules. This specification below lists current specified is for the ACPS3310 carrier board only.

+12 Volts ($\pm 8\%$) 0.290A Typical

Add the current for each of the AcroPack modules to calculate the total current required from each supply. The carrier is designed to provide the following voltage and currents to each AcroPack module.

Supply Voltage	Current (Max)
+12V +/- 8% (max)	0.5 A
-12V +/- 8% (max)	0.5 A
+5V +/- 5% (max)	0.5 A
+3.3V +/- 5% (max)	1.1 A
+1.5V +/- 5% (max)	0.5 A
+3.3Vaux +/- 9% (max)	100mA

The carrier board provides +1.5V, +3.3V, +5V, +12V and -12V power to each AcroPack module. The ACPC3310 utilizes DC/DC converters to generate the +1.5V, +3.3V, +5V and -12V supplies from the +12V on the CPCI-S backplane. An additional regulator and fuse can be populated to supply +3.3Vaux from the +5V standby on the CPCI-S backplane.

Fuses

+1.5 1.1 Amps (F5, F10) Raychem NANOSMDC110F-2
 +3.3V 3 Amps (F4, F9) Littelfuse 0466003.NR
 +5V, +12V, -12V 2 Amps (F1, F2, F3, F6, F7, F8) Littelfuse 0453002.MR

CPCI-S COMPLIANCE

Specification.....This device meets or exceeds all written CompactPCI Serial specifications per revision 2.0. (PICMG CPCI-S.0 R2.0)

ENVIRONMENTAL

Operating Temperature.....-40 to +85°C (with 200 LFM airflow)

Relative Humidity.....5-95% non-condensing

Storage Temperature.....-55 to +125°C.

EMC Compliance

The ACPS3310 complies with EMC Directive 2004/108/EC.

Immunity.....per EN 61000-6-2

Electrostatic Discharge Immunity (ESD), per IEC 61000-4-2

Radiated Field Immunity (RFI), per IEC 61000-4-3

Electrical Fast Transient Immunity (EFT), per IEC 61000-4-4

Surge Immunity, per IEC 61000-4-5

Conducted RF Immunity (CRFI), per IEC 61000-4-6

Emissionsper EN61000-6-4

Enclosure Port, per CISPR 16

Low Voltage AC Mains Port, per CISPR 16

Note: This is a Class A product

Vibration and Shock Standard

The ACPS3310 is designed to pass the following Vibration and Shock standards.

Vibration, Sinusoidal Operating.....Designed to comply with IEC 60068-2-6: 10-500Hz, 5G, 2 Hours/axis

Vibration, Random Operating.....Designed to comply with IEC 60068-2-64: 10-500Hz, 5G-rms, 2 Hours/axis

Shock, Operating.....Designed to comply with IEC 60068-2-27: 30G, 11ms half sine, 50G, 3ms half sine, 18 shocks at 6 orientations for both test levels

Reliability Prediction

MTBF (Mean Time Between Failure): MTBF in hours using MIL-HDBK-217F, FN2. *Per MIL-HDBK-217, Ground Benign, Controlled, $G_B G_C$*

Temperature	MTBF (Hours)	MTBF (Years)	Failure Rate (FIT ¹)
25°C	1,808,763	206.5	552.9
40°C	1,103,975	126.0	905.8

¹ FIT is Failures in 10⁹ hours.

6. CERTIFICATE OF VOLATILITY

Certificate of Volatility				
Acromag Model ACPS3310		Manufacturer: Acromag, Inc. 30765 Wixom Rd Wixom, MI 48393		
Volatile Memory				
Does this product contain Volatile memory (i.e. Memory of whose contents are lost when power is removed) <input type="checkbox"/> Yes <input checked="" type="checkbox"/> No				
Non-Volatile Memory				
Does this product contain Non-Volatile memory (i.e. Memory of whose contents is retained when power is removed) <input checked="" type="checkbox"/> Yes <input type="checkbox"/> No				
Type (EEPROM, FLASH etc.)	Size:	User Modifiable	Function:	Process to Sanitize:
FLASH	1 Mbit	Yes	PCIe switch configuration	Overwrite FLASH contents.
Acromag Representative				
Name:	Title:	Email:	Office Phone:	Office Fax:
Russ Nieves	Director of Sales and Marketing	rnieves@acromag.com	248-295-0838	248-624-9234

7. REVISION HISTORY

The following table shows the revision history for this document:

Release Date	Version	EGR/DOC	Description of Revision
26-JUL-2018		ENZ	Preliminary release.
23-APR-2019	A	ENZ/ARP	Release.